

Сечение провода, мм ²	Диаметр под винт	Размеры, мм						Упаковка, шт.	Код
		C2	C1	L	A	B	D		
35	5	9	11,5	6	14	17	5,5	100	2G5C
	6			6		17	6,5	100	2G6C
	8			8		17	8,4	100	2G8C
	10			10		18	10,5	100	2G10C
	12			12		19	13	100	2G12C
	14			14		21	15	100	2G14C
	16			16		23	17	100	2G16C
	6	10	13	6,5	15	20	6	50	2H6C
	8			8		20	9	50	2H8C
	10			10		20	11	50	2H10C
50	12	10	13	12	15	20	13	50	2H12C
	14			14		21	15	50	2H14C
	16			16		22	17	50	2H16C
70	6	12	15	7	18	22	6,6	50	2I6C
	8			9,5		22	9	50	2I8C
	10			10,5		22	11	50	2I10C
	12			12		22	13	50	2I12C
	14			14		22	15	50	2I14C
	16			15		23	17	50	2I16C
	18			18		24	19	50	2I18C
	20			20		27	21	50	2I21C
95	6	13,7	17,1	9	20	26	6,6	25	2L6C
	8			9,5			9	25	2L8C
	10			10,5			11	25	2L10C
	12			12,5			13	25	2L12C
	14			14			15	25	2L14C
	16			16			17	25	2L16C
	18			18			19	25	2L18C
	20			22			21	25	2L21C
120	8	15	19,6	8	22,5	29	9	25	2M8C
	10			11			11	25	2M10C
	12			13			13	25	2M12C
	16			16			17	25	2M16C
	18			18			19	25	2M18C
	20			20			21	25	2M21C
150	8	16,7	21,5	8	25	32	9	20	2N8C
	10			10			11	20	2N10C
	12			12			13	20	2N12C
	14			14			15	20	2N14C
	16			16			17	20	2N16C
	18			18			19	20	2N18C
	20			20			21	20	2N21C
185	10	19,2	24,4	11	28	36	11	10	2O10C
	12			12			13	10	2O12C
	14			14			15	10	2O14C
	16			16			17	10	2O16C
	18			18			19	10	2O18C
	20			19			22	10	2O21C
300	12	23,7	30,6	12	28	36	13	10	2Q12C
400	20	27	35	20			22	5	2R21C